

PRODUCT-DETAILS

ESB63-40N-07

ESB63-40N-07 Installation Contactor (NO) 63 A - 4 NO - 0 NC - 400 V - Control Circuit 400 Hz



Extended Product Type	ESB63-40N-07
Product ID	1SAE351111R0740
EAN	4013614519291
Catalog Description	ESB63-40N-07 Installation Contactor (NO) 63 A - 4 NO - 0 NC - 400 V - Control Circuit 400 Hz
Long Description	The ESB63N installation contactors are used to control single and three-phase loads up to 63 A and can be operated by AC or DC.
	These contactors are made for use in household applications as well as in industrial environments
	The following benefits are provided:
	Hum-free operation, low power consumption and integrated overvoltage protection. Various contact combinations and accessories are available

Ordering	
Package Level 1 EAN	4013614525605
Minimum Order Quantity	1 piece
Customs Tariff Number	85365080

Popular Downloads	
Data Sheet, Technical Information	2CDC103051C0201
Instructions and Manuals	2CDC103043M6801

CAD Dimensional 2CDC001079B0201
Drawing 2CDC001079B0201

Dimensions	
Product Net Width	54 mm
Product Net Height	85 mm
Product Net Depth / Length	65 mm
Product Net Weight	0.4 kg

Technical		
Rated Operational Voltage		Main Circuit 220 V DC Main Circuit 400 V AC
Rated Control Circuit Voltage (U _c)		400 V
Rated Frequency (f)		Control Circuit 400 Hz Control Circuit 50 Hz Control Circuit 60 Hz Control Circuit DC Main Circuit 50 Hz Main Circuit 60 Hz Main Circuit DC
Rated Operational Current AC-1 (I _e)		(NO) 63 A
Rated Operational Current AC-3 (I _e)		30 V) Single Phase, NO 30 A 100 V) Three Phase, NO 30 A
Rated Operational Power AC-1 (P _e)		V) Single Phase, NO 14.5 kW V) Three Phase, NO 43.6 kW
Rated Operational Power AC-3 (P _e)		30 V) Single Phase, NO 5 kW 0 V) Three Phase, NO 15 kW
Rated Operational Current AC-7a (I _e)		(NO) 63 A
Rated Operational Power AC-7a (P _e)		V) Single Phase, NO 14.5 kW V) Three Phase, NO 43.6 kW
Rated Operational Current AC-7b (I _e)		30 V) Single Phase, NO 30 A 400 V) Three Phase, NO 30 A
Rated Operational Power AC-7b (P _e)		30 V) Single Phase, NO 5 kW 0 V) Three Phase, NO 15 kW
Recommended Screw Driver		Control Circuit Pozidriv 1 Main Circuit Pozidriv 2
Rated Impulse Withstand Voltage (U _{imp})		6 k\
Rated Insulation Voltage (U_i)		500 V
Connecting Capacity Main Circuit	Flexible Flexible with Insula	with Ferrule 1x 1.5 16 mm with Ferrule 2x 1.5 10 mm ated Ferrule 1x 1.5 16 mm ated Ferrule 2x 1.5 10 mm Flexible 2x 1.5 10 mm Flexible 1x 1.5 16 mm Rigid 1x 1.5 25 mm Rigid 2x 1.5 10 mm
Connecting Capacity Control Circuit	Flexible wi Flexible with Insulate	ith Ferrule 1x 0.75 2.5 mm ith Ferrule 2x 0.75 1.0 mm ed Ferrule 1x 0.75 2.5 mm ated Ferrule 2x 0.75 1 mm Flexible 1x 1 4.0 mm Flexible 2x 1 2.5 mm Rigid 1x 1 4 mm Rigid 2x 1 2.5 mm
Tightening Torque		Control Circuit 0.9 N·m Main Circuit 2.5 N·m
Wire Stripping Length		Control Circuit 7 mm Main Circuit 13 mm
© 2024 ABB All rights reserved	2024/01/00	Subject to char

Degree of Protection	IP20
Electrical Durability	AC-1 (NO) 100000 cycle AC-3 (NO) 240000 cycle AC-7a (NO) 100000 cycle AC-7b (NO) 240000 cycle
Mechanical Durability	1000000 cycle
Number of Poles	4
Number of Auxiliary Contacts NC	0
Number of Auxiliary Contacts NO	0
Number of Main Contacts NC	0
Number of Main Contacts NO	4
Width in Number of Modular Spacings	3
Pollution Degree	3
Standards	IEC/EN 60947-1 IEC/EN 60947-4-1 IEC/EN 61095 UL 60947-1 UL 60947-4-1

Technical UL/CSA	
Maximum Operating Voltage UL/CSA	Main Circuit 480 V AC
Horsepower Rating UL/CSA	(220 240 V AC) Single Phase, NO 5 Hp (220 240 V AC) Three Phase, NO 10 Hp (440 480 V AC) Single Phase, NO 7.5 Hp (440 480 V AC) Three Phase, NO 15 Hp
Connecting Capacity Main Circuit UL/CSA	Solid 16-4 AWG Stranded 16-4 AWG
Connecting Capacity Control Circuit UL/CSA	Solid 16-10 AWG Stranded 16-10 AWG
Tightening Torque UL/CSA	Control Circuit 8 in·lb Main Circuit 20 in·lb

Environmental	
Ambient Air Temperature	Operation -25 +55 °C Storage -40 +80 °C
Maximum Operating Altitude Permissible	2000 m
Resistance to Shock acc. to IEC 60068-2-27	11 ms Pulse 15g
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019

Certificates and Declarations	
ABS Certificate	1SAA920000-0101
CB Certificate	1SAA920005-2001
CQC Certificate	CQC2017010304993562 CQC2017010304993563
Declaration of Conformity - CCC	2020980304001310 2020980304001313
Declaration of Conformity - CE	1SAD101100-3301
Declaration of Conformity - UKCA	1SAD201100-3301
DNV Certificate	1SAA920000-0306
EAC Certificate	1SAA920001-2702
NF Certificate	1SAA920001-1202

 RINA Certificate
 1SAA920000-0801

 RMRS Certificate
 1SAA920000-0705

 UL Certificate
 E191658-19960301

Package Level 1 Units	1 piece
Package Level 1 Width	92 mm
Package Level 1 Height	69.5 mm
Package Level 1 Depth / Length	57 mm
Package Level 1 Gross Weight	0.4 kg
Package Level 1 EAN	4013614525605
Package Level 2 Units	32 piece
Package Level 2 Width	280 mm
Package Level 2 Height	210 mm
Package Level 2 Depth / Length	395 mm
Package Level 2 Gross Weight	13.3 kg
Package Level 2 EAN	4013614540004

Classifications	
Object Classification Code	Q
ETIM 5	EC001653 - Installation contactor for distribution board
ETIM 6	EC001653 - Installation contactor for distribution board
ETIM 7	EC001653 - Installation contactor for distribution board
eClass	V11.0 : 27142308
UNSPSC	39121529
IDEA Granular Category Code (IGCC)	4759 >> Installation contactor for distribution board
ETIM 8	EC001653 - Installation contactor for distribution board

Accessories				
Identifier	Description	Туре	Quantity	Unit Of Measure
1SAE901901R1011	EH04-11N Auxiliary Contact	EH04-11N	1	piece
1SAE901901M1011	EH04-11N Auxiliary Contact	EH04-11N	1	piece
1SAE901901R1020	EH04-20N Auxiliary Contact	EH04-20N	1	piece
1SAE901901M1020	EH04-20N Auxiliary Contact	EH04-20N	1	piece
GHE3401903R0001	ESB-PLK40/63 Sealing Cover ES	SB-PLK40/63	1	piece
GHE3201902R0001	ESB-DIS Distance Piece	ESB-DIS	1	piece

Categories

 $Low\ Voltage\ Products\ and\ Systems\ \rightarrow\ Control\ Products\ \rightarrow\ Contactors\ \rightarrow\ Installation\ Contactors$ $Low\ Voltage\ Products\ and\ Systems\ \rightarrow\ Modular\ DIN\ Rail\ Products\ \rightarrow\ Command\ and\ Signalling\ Devices\ \rightarrow\ Installation\ Contactors$

